© 2009 Sudarshan S. Chawathe

Name:			
rame.			

This assignment focuses on *hashing*, described in Chapter 20 of the textbook. Please refer to the previous assignments for important instructions on the allowable use of resources and the requirements for electronic submission.

- 1. (1 pt.) Write your name in the space provided above.
- 2. (1 pt.) Package your solutions to the programming questions as in previous assignments. Submit your work via http://cs.umaine.edu/~chaw/u/. After submitting your work, complete the following:

File name: Size, in bytes: _______
MD5 checksum: ______
Timestamp: ______

3. (6 pts.) Compare search trees and hashing as data structures for collections of keys by naming (1) three operations that are supported by both and (2) three operations that are supported by search trees, but not by hashing.

4. (6 pts.) Refer to the simple method for storing a set of 16-bit integers described at the beginning of Section 20.1. How much storage (in bytes) would be required if that method were used for 64-bit integers? Explain how you arrive at your answer.

5.	(6 pts.) The book notes that a hash table may be used to implement a set in constant time per operation. Name three set operations that a hash-table may implement in constant time. Name three set operations that a hash table cannot implement (easily) in constant time. Justify your answers.
6.	(6 pts.) What is the maximum number of collisions that may result from hashing n keys? Provide an explicit hash function that produces this number of collisions.
7.	(6 pts.) If a hash table H of size m contains n keys, what are the minimum and maximum number of probes required to insert a new key into H ? Justify your answer.

8. (8 pts.) Using the method of the fourth paragraph of Section 20.1, map each of the seven strings All your base are belong to us. (including the period) to integers. You may use a calculator or computer but must show your work for at least the string base. Assume a 7-bit ASCII character encoding; for convenience, a table of codes appears below. Note that there can be no partial credit awarded if you arrive at a wrong answer and do not show your work.

```
O NUL
          16 DLE
                             48 0
                                                      96'
                    32
                                     64 @
                                             80 P
                                                             112 p
                                                             113 q
 1 SOH
          17 DC1
                    33 !
                             49 1
                                     65 A
                                             81 Q
                                                      97 a
                    34 "
 2 STX
          18 DC2
                             50 2
                                     66 B
                                             82 R
                                                      98 b
                                                             114 r
                    35 #
                                                      99 c
3 ETX
          19 DC3
                             51 3
                                     67 C
                                             83 S
                                                             115 s
 4 EOT
          20 DC4
                    36 $
                             52 4
                                     68 D
                                             84 T
                                                     100 d
                                                             116 t
          21 NAK
                    37 %
                             53 5
                                     69 E
                                             85 U
5 ENQ
                                                     101 e
                                                             117 u
          22 SYN
                    38 &
                                     70 F
 6 ACK
                             54 6
                                             86 V
                                                     102 f
                                                             118 v
                    39 '
                             55 7
7 BEL
          23 ETB
                                     71 G
                                             87 W
                                                     103 g
                                                             119 w
8 BS
                                             88 X
          24 CAN
                    40 (
                             56 8
                                     72 H
                                                     104 h
                                                             120 x
9 HT
          25 EM
                    41 )
                             57 9
                                     73 I
                                              89 Y
                                                     105 i
          26 SUB
                             58 :
                                                     106 ј
10 LF
                    42 *
                                     74 J
                                             90 Z
                                                             122 z
11 VT
          27 ESC
                    43 +
                             59;
                                     75 K
                                             91 [
                                                     107 k
                                                             123 {
                             60 <
12 FF
          28 FS
                    44 ,
                                     76 L
                                             92 \
                                                     108 1
                                                             124 l
                             61 =
13 CR
          29 GS
                    45 -
                                     77 M
                                             93 ]
                                                     109 m
                                                             125 }
14 SO
          30 RS
                    46 .
                             62 >
                                     78 N
                                             94 ^
                                                     110 n
                                                             126 ~
                                             95 _
15 SI
          31 US
                    47 /
                             63 ?
                                     79 0
                                                     111 o
                                                             127 DEL
```

9. (8 pts.) Repeat Question 8 using the hash function of Figure 20.1. You may use a calculator or computer but must show your work by indicating the value of hashVal at the end of each iteration of the for loop for at least the string base.

 $10.\ (8\ \mathrm{pts.})$ Repeat Question 9 for the hash function of Figure 20.2.

 $11.\ (8\ \mathrm{pts.})$ Repeat Question 10 for the hash function of Figure 20.3.

12. (4 pts.) Suppose we are writing code that must run in a programming environment that supports only addition and shifting of 16-bit binary numbers. Provide efficient pseudocode for this environment that is equivalent to line 12 of Figure 20.2 in the textbook.

13. (8 pts.) Using Figure 20.4 in the textbook as a template, depict the result of inserting the seven strings of Question 8 into a hash table of size 17, using each of the three hash functions noted in Questions 9, 10, and 11. Use the linear probing method for collision resolution.

 $14. \ (8 \mathrm{\ pts.})$ Repeat Question 13 using the quadratic probing method for collision resolution.

 $15. \ (8 \mathrm{\ pts.})$ Repeat Question 13 using the separate chaining method for collision resolution,

and a hash table of size 11.

16. (8 pts.) Consider the following modification of the separate chaining method, yielding a method called *coalesced hashing*: Instead of using separate storage for the linked lists used by separate chaining, the linked lists are stored in the otherwise unused slots of the hash table. With this method, each slot in the hash table contains either a key (as in linear or quadratic probing) or a cell belonging to a linked list that is used for chaining (as in separate chaining). Note that the linked-list cell occupying a hash table slot does not necessarily contain a key that hashes to that slot.

Repeat Question 13 using this coalesced chaining method for collision resolution.

17. (100 pts.) Modify the textbook's implementation of the HashSet class¹ to use the coalesced hashing technique of Question 16 instead of quadratic probing. You may use as much or as little of the textbook's code as you wish (with proper attribution, as always) but your implementation of HashSet must be completely interchangeable with the textbook's implementation. That is, any program that uses the textbook's implementation should work as before if all the files implementing the textbook's HashSet class are replaced with those implementing yours (with no other changes).

¹Mark Allen Weiss, *Data Structures and Problem Solving Using Java*, 3rd edition (Addison-Wesley, 2006), Section 20.4.1, pp. 727–733.